2MBI1400XXB120P-50

IGBT Modules

Power Module (X series)
1200V / 1400A / 2-in-1 package



■ Features

Low $V_{CE(sat)}$
Low Inductance Module structure

■ Applications

Inverter for Motor Drives, AC and DC Servo Drives
Uninterruptible Power Supply Systems, Wind Turbines, PV Power Conditioning Systems

■ Outline drawing (Unit : mm)



Weight: 1250 g(typ.)

■ Equivalent circuit



FM5F9460a
2023/11

2MBI1400XXB120P-50

■ Absolute maximum ratings (at T_c= 25°C unless otherwise specified)

Items			Symbols	Conditions		Maximum ratings	Units
Inverter	Collector-Emitter voltage, Gate-Emitter short-circuited		V_{CES}			1200	V
	Gate-Emitter voltage, Collector-Emitter short-circuited		V_{GES}			±20	V
	Collector current		I_C	Continuous	T_c=100°C	1400	A
	Repetitive peak collector current		I_{CRM}	1ms		2800	
	Forward current		I_F			1400	
	Repetitive peak forward current		I_{FRM}	1ms		2800	
	Total power dissipation		P_{tot}	1 device		5.4	kW
	Virtual junction temperature		T_{vj}			175	°C
	Operating virtual junction temperature (under switching conditions)		T_{vjop}			175	
Case temperature			T_c			150	
Storage temperature			T_{stg}			-40 ~ 150	
Isolation voltage		Between terminal and copper base (*1)	V_{isol}	AC: 1min.		4000	Vrms
		Between thermistor and others (*2)					
Mounting torque of screws to heatsink			M_s	M5		3.0～6.0	N·m
Mounting torque of screws to main terminals			M_t	M8		8.0～10.0	
Mounting torque of screws to sense terminals				M4		1.8～2.1	

(*1) All terminals should be connected together during the test.
(*2) Two thermistor terminals should be connected together, other terminals should be connected together and shorted to base plate during the test.

2MBI1400XXB120P-50

■ Electrical characteristics (at T_{vj}= 25°C unless otherwise specified)

	Items	Symbols	Conditions		Characteristics min.	Characteristics typ.	Characteristics max.	Units
Inverter	Collector-Emitter cut-off current, Gate-Emitter short-circuited	I_{CES}	V_{GE} = 0V V_{CE} = 1200V		-	-	600	μA
	Gate leakage current, Collector-Emitter short-circuited	I_{GES}	V_{CE}=0V, V_{GE}=±20V		-	-	1200	nA
	Gate-Emitter threshold voltage	$V_{GE(th)}$	V_{CE} = 20V I_C = 1400mA		6.0	6.5	7.0	V
	Collector-Emitter saturation voltage	$V_{CE(sat)}$ (terminal)	V_{GE} = 15V I_C= 1400A	T_{vj}=25°C	-	1.50	1.95	V
		$V_{CE(sat)}$ (chip)		T_{vj}=25°C	-	1.45	1.90	
				T_{vj}=125°C	-	1.70	-	
				T_{vj}=150°C	-	1.80	-	
				T_{vj}=175°C	-	1.85	-	
	Internal gate resistance	r_g	-		-	2.50	-	Ω
	Capacitance	C_{ies}	V_{CE}=10V, V_{GE}=0V, f=1MHz		-	147	-	nF
		C_{oes}			-	5.0	-	
		C_{res}			-	1.3	-	
	Gate charge	Q_G	V_{CC} = 600V, I_C = 1400A V_{GE} = -15 → +15V		-	9.5	-	μC
	Forward voltage	V_F (terminal)	V_{GE} = 0V I_F= 1400A	T_{vj}=25°C	-	1.70	2.15	V
		V_F (chip)		T_{vj}= 25°C	-	1.65	2.10	
				T_{vj}=125°C	-	1.70	-	
				T_{vj}=150°C	-	1.65	-	
				T_{vj}=175°C	-	1.65	-	
	Switching time (*1)	$t_{d(on)}$	V_{CC} = 600V I_C, I_F = 1400A V_{GE} = +15/-15 V $R_{G(on/off)}$ = 0.68/0.68 Ω L_S = 40 nH	T_{vj}= 25°C	-	1.10	-	μs
				T_{vj}=125°C	-	1.10	-	
				T_{vj}=150°C	-	1.10	-	
				T_{vj}=175°C	-	1.10	-	
		t_r		T_{vj}= 25°C	-	0.20	-	
				T_{vj}=125°C	-	0.22	-	
				T_{vj}=150°C	-	0.22	-	
				T_{vj}=175°C	-	0.22	-	
		$t_{d(off)}$		T_{vj}= 25°C	-	0.90	-	
				T_{vj}=125°C	-	0.94	-	
				T_{vj}=150°C	-	0.96	-	
				T_{vj}=175°C	-	0.97	-	
		t_f		T_{vj}= 25°C	-	0.16	-	
				T_{vj}=125°C	-	0.17	-	
				T_{vj}=150°C	-	0.18	-	
				T_{vj}=175°C	-	0.20	-	
	Reverse recovery time	t_{rr}		T_{vj}= 25°C	-	0.29	-	
				T_{vj}=125°C	-	0.47	-	
				T_{vj}=150°C	-	0.49	-	
				T_{vj}=175°C	-	0.52	-	

(*1) Turn on time (t_{on}) = $t_{d(on)}$+ t_r , Turn off time (t_{off}) = $t_{d(off)}$ + t_f

2MBI1400XXB120P-50

■ Electrical characteristics (at T_{vj}= 25°C unless otherwise specified)

Items		Symbols	Conditions		Characteristics min.	Characteristics typ.	Characteristics max.	Units
Inverter	Switching loss (per pulse)	E_{on}	V_{CC} = 600V, I_C, I_F = 1400A, V_{GE} = +15/-15 V, $R_{G(on/off)}$ = 0.68/0.68 Ω, L_S = 40 nH	T_{vj}= 25°C	-	128	-	mJ
				T_{vj}=125°C	-	193	-	
				T_{vj}=150°C	-	201	-	
				T_{vj}=175°C	-	216	-	
		E_{off}		T_{vj}= 25°C	-	191	-	
				T_{vj}=125°C	-	243	-	
				T_{vj}=150°C	-	257	-	
				T_{vj}=175°C	-	265	-	
		E_{rr}		T_{vj}= 25°C	-	55	-	
				T_{vj}=125°C	-	87	-	
				T_{vj}=150°C	-	103	-	
				T_{vj}=175°C	-	114	-	
Thermistor	Resistance	R	T = 25°C		-	5000	-	Ω
			T = 100°C		465	495	520	
	B value	B	T = 25/ 50°C		3305	3375	3450	K

NOTICE:
The external gate resistance (R_G) shown above is one of our recommended value for the purpose of minimum switching loss. However the optimum R_G depends on circuit configuration and/or environment. We recommend that the R_G has to be carefully chosen based on consideration if IGBT module matches design criteria, for example, switching loss, EMC/EMI, spike voltage, surge current and no unexpected oscillation and so on.

■Thermal resistance characteristics

Items	Symbols	Conditions	Characteristics min.	Characteristics typ.	Characteristics max.	Units
Thermal resistance junction to case(1 device)	$R_{th(j-c)}$	Inverter IGBT	-	-	27.5	K/kW
		Inverter FWD	-	-	48.0	
Thermal resistance case to heatsink(1 IGBT+1 FWD) (*1)	$R_{th(c-s)}$	with 1 W/(m·K) thermal grease	-	4.2	-	

(*1) This is the value which is defined mounting on the additional heatsink with thermal grease.

[Inverter]
Collector current vs. Collector-Emitter voltage (typ.)
T_{vj} = 25°C / chip



[Inverter]
Collector current vs. Collector-Emitter voltage (typ.)
T_{vj} = 175°C / chip



[Inverter]
Collector current vs. Collector-Emitter voltage (typ.)
V_{GE} = 15V / chip



[Inverter]
Collector-Emitter voltage vs. Gate-Emitter voltage (typ.)
T_{vj} = 25°C / chip



[Inverter]
Capacitance vs. Collector-Emitter voltage (typ.)
V_{GE} = 0V, f = 1MHz, T_{vj} = 25°C



[Inverter]
Dynamic gate charge (typ.)
V_{CC} = 600V, I_C = 1400A, T_{vj} = 25°C



2MBI1400XXB120P-50

[Inverter]
E_{on} vs. Collector current (typ.)
V_{CC}= 600V, V_{GE} = +15/-15 V, $R_{G(on/off)}$= 0.68/0.68 Ω



[Inverter]
E_{on} vs. Gate resistance (typ.)
V_{CC}= 600V, V_{GE} = +15/-15 V, I_C= 1400A



[Inverter]
E_{off} vs. Collector current (typ.)
V_{CC}= 600V, V_{GE} = +15/-15 V, $R_{G(on/off)}$= 0.68/0.68 Ω



[Inverter]
E_{off} vs. Gate resistance (typ.)
V_{CC}= 600V, V_{GE} = +15/-15 V, I_C= 1400A



[Inverter]
E_{rr} vs. Forward current (typ.)
V_{CC}= 600V, V_{GE} = +15/-15 V, $R_{G(on/off)}$= 0.68/0.68 Ω



[Inverter]
E_{rr} vs. Gate resistance (typ.)
V_{CC}= 600V, V_{GE} = +15/-15 V, I_F= 1400A



2MBI1400XXB120P-50

[Inverter]
Switching time vs. Collector current (typ.)
V_{CC} = 600V, $R_{G\ (on/off)}$ = 0.68/0.68 Ω, V_{GE} = +15/-15 V, T_{vj} = 25°C



[Inverter]
Switching time vs. Gate resistance (typ.)
V_{CC} = 600V, I_C = 1400A, V_{GE} = +15/-15 V, T_{vj} = 25°C



[Inverter]
Switching time vs. Collector current (typ.)
V_{CC} = 600V, $R_{G\ (on/off)}$ = 0.68/0.68 Ω, V_{GE} = +15/-15 V, T_{vj} = 175°C



[Inverter]
Switching time vs. Gate resistance (typ.)
V_{CC} = 600V, I_C = 1400A, V_{GE} = +15/-15 V, T_{vj} = 175°C



[Inverter]
Reverse bias safe operating area (max.)
V_{GE} = +15/-15 V, $R_{G(off)} \geqq 0.68\Omega$, T_{vj} = 175°C



2MBI1400XXB120P-50

[Inverter]
Forward current vs. Forward voltage (typ.)
chip



[Inverter]
Reverse recovery characteristics (typ.)
V_{CC} = 600V, V_{GE} = +15/-15 V, $R_{G(on/0ff)}$ = 0.68/0.68 Ω



[Inverter]
FWD safe operation area (max.)
T_{vj} = 175°C



[Inverter]
Transient thermal impedance (max.)



n		1	2	3	4
τ_n	[sec]	0.0023	0.0301	0.0598	0.0708
r_n [K/kW]	IGBT	2.9497	7.4785	10.5649	6.5069
	FWD	5.1485	13.0533	18.4406	11.3575

[Thermistor]
Temperature characteristic (typ.)



Warnings

1. This Catalog contains the product specifications, characteristics, data, materials, and structures as of 11/2023. The contents are subject to change without notice for specification changes or other reasons. When using a product listed in this Catalog, be sure to obtain the latest specifications.

2. All applications described in this Catalog exemplify the use of Fuji's products for your reference only. No right or license, either express or implied, under any patent, copyright, trade secret or other intellectual property right owned by Fuji Electric Co., Ltd. is (or shall be deemed) granted. Fuji Electric Co., Ltd. makes no representation or warranty, whether express or implied, relating to the infringement or alleged infringement of other's intellectual property rights which may arise from the use of the applications described herein.

3. Although Fuji Electric Co., Ltd. is enhancing product quality and reliability, a small percentage of semiconductor products may become faulty. When using Fuji Electric semiconductor products in your equipment, you are requested to take adequate safety measures to prevent the equipment from causing a physical injury, fire, or other problem if any of the products become faulty. It is recommended to make your design fail-safe, flame retardant, and free of malfunction.

4. The products introduced in this Catalog are intended for use in the following electronic and electrical equipment which has normal reliability requirements.
・Computers ・OA equipment ・Communications equipment (terminal devices) ・Measurement equipment
・Machine tools ・Audiovisual equipment ・Electrical home appliances ・Personal equipment ・Industrial robots etc.

5. If you need to use a product in this Catalog for equipment requiring higher reliability than normal, such as for the equipment listed below, it is imperative to contact Fuji Electric Co., Ltd. to obtain prior approval. When using these products for such equipment, take adequate measures such as a backup system to prevent the equipment from malfunctioning even if a Fuji's product incorporated in the equipment becomes faulty.
・Transportation equipment (mounted on cars and ships) ・Trunk communications equipment
・Traffic-signal control equipment ・Gas leakage detectors with an auto-shut-off feature
・Emergency equipment for responding to disasters and anti-burglary devices ・Safety devices ・Medical equipment

6. Do not use products in this Catalog for the equipment requiring strict reliability such as the following and equivalents to strategic equipment (without limitation).
・Space equipment ・Aeronautic equipment ・Nuclear control equipment ・Submarine repeater equipment

7. Copyright (c)1996-2023 by Fuji Electric Co., Ltd. All rights reserved.
No part of this Catalog may be reproduced in any form or by any means without the express permission of Fuji Electric Co., Ltd.

8. If you have any question about any portion in this Catalog, ask Fuji Electric Co., Ltd. or its sales agents before using the product. Neither Fuji Electric Co., Ltd. nor its agents shall be liable for any injury caused by any use of the products not in accordance with instructions set forth herein.

富士電機 Innovating Energy Technology

Technical Information

IGBT Modules

- Please refer to URLs below for futher information about products, application manuals and design support.
- 关于本规格书中没有记载的产品信息，应用手册，技术信息等，请参考以下链接。
- 本データシートに記載されていない製品情報，アプリケーションマニュアル，デザインサポートは以下のURLをご参照下さい。

FUJI ELECTRIC Power Semiconductor WEB site

日本	www.fujielectric.co.jp/products/semiconductor/
Global	www.fujielectric.com/products/semiconductor/
中国	www.fujielectric.com/products/semiconductor/cn/
Europe	www.fujielectric-europe.com/products/semiconductors/
North America	www.americas.fujielectric.com/products/semiconductors/

Information

日本	
1 半導体総合カタログ	www.fujielectric.co.jp/products/semiconductor/catalog/
2 製品情報	www.fujielectric.co.jp/products/semiconductor/model/
3 アプリケーションマニュアル	www.fujielectric.co.jp/products/semiconductor/model/igbt/application/
4 デザインサポート	www.fujielectric.co.jp/products/semiconductor/model/igbt/technical/
5 マウンティングインストラクション	www.fujielectric.co.jp/products/semiconductor/model/igbt/mounting/
6 IGBT 損失シミュレーションソフト	www.fujielectric.co.jp/products/semiconductor/model/igbt/simulation/
7 富士電機技報	www.fujielectric.co.jp/products/semiconductor/journal/
8 製品のお問い合わせ	www.fujielectric.co.jp/products/semiconductor/contact/

Global	
1 Semiconductors General Catalog	www.fujielectric.com/products/semiconductor/catalog/
2 Product Information	www.fujielectric.com/products/semiconductor/model/
3 Application Manuals	www.fujielectric.com/products/semiconductor/model/igbt/application/
4 Design Support	www.fujielectric.com/products/semiconductor/model/igbt/technical/
5 Mounting Instructions	www.fujielectric.com/products/semiconductor/model/igbt/mounting/
6 IGBT Loss Simulation Software	www.fujielectric.com/products/semiconductor/model/igbt/simulation/
7 Fuji Electric Journal	www.fujielectric.com/products/semiconductor/journal/
8 Contact	www.fujielectric.com/contact/

中国	
1 半导体综合目录	www.fujielectric.com/products/semiconductor/cn/catalog/
2 产品信息	www.fujielectric.com/products/semiconductor/cn/model/
3 应用手册	www.fujielectric.com/products/semiconductor/cn/model/igbt/application/
4 技术信息	www.fujielectric.com/products/semiconductor/cn/model/igbt/technical/
5 安装说明书	www.fujielectric.com/products/semiconductor/cn/model/igbt/mounting/
6 IGBT 损耗模拟软件	www.fujielectric.com/products/semiconductor/cn/model/igbt/simulation/
7 富士电机技报	www.fujielectric.com/products/semiconductor/cn/journal/
8 产品咨询	www.fujielectric.com/contact/